

If Problems: Check that correct adapter has been used and links are in the correct place. Always disconnect from the power supply if you change the head-unit adapter lead. Check that Red wire is 12V ignition and not Permanent power. Check that head-unit is earthed and black wire is earth. Check all connections are the same as the wiring diagram shown here

Choose a head-unit adapter from the list overleaf and connect it to the USC black box.

Check that the red wire is a 12V IGNITION source in the car then turn on ignition

Remove the OEM head-unit and identify the 14 way audio connector and ensure it mates

Identify the 10 way connector and connect White to Pink and Purple to Blue wires as shown.

Turn off the ignition supply to the car!

Test unit before fully fitting radio and trims back.

correctly with the connector supplied with the 29 series cable.

1.

2.

3.

4.

5.

6.

1st

RC

Check to ensure that the

USC 16 pin connector is

wired as above

+12v -12v IGN GND RC1

Car identity

Donale



